



Specification

PSI 4000

Phase Sequence Indicator



Measurement Principle is Static Induction

Input Voltage: 150V – 1000V 3-Phase AC.

Frequency Range: 45-65Hz

Operating Temperature & Humidity: -10°C to 50°C, Max. 80% RH.

Battery Current consumption: 15mA

Cable Length: Approx. 800 mm

Power Source: 1.5V X 4 (AA or LR6) alkaline batteries

Auto-Off: After 5 mins of non activity

Low Battery Warning: Power LED flashes below 4.6V DC battery voltage

Safety standard: EN 61010-1 CAT III 1000V, CAT IV 600V. EN 61326-1.

Weight: Approx. 370 g (batteries included)

Dimensions: 118 (L) x 69 (W) x 38 (H) mm

Accessories: Instruction manual, soft case, batteries.

Check out what else you can get from Martindale:

- 17th Edition Testers
- Accessories
- Calibration Equipment
- Continuity Testers
- Electricians' Kits
- Environmental Products
- Full Calibration & Repair Service
- Fuse Finders
- Digital Clamp Meters
- Digital Multimeters
- Labels
- Microwave Leakage Detectors
- Motor Maintenance Equipment
- Multifunction Testers
- Non-trip Loop Testers
- Pat Testers & Accessories
- Phase Rotation Testers
- Proving Units
- Socket Testers
- Thermometers & Probes
- Test Leads
- Voltage Indicators
- Specialist Metrohm Testers (4 & 5kV)
- Specialist Drummond Testers



Martindale Electric Company Limited
Metrohm House, Penfold Trading Estate, Imperial Way, Watford WD24 4YY, UK
Tel: +44(0)1923 441717 Fax: +44 (0)1923 446900
E-mail: sales@martindale-electric.co.uk
Website: www.martindale-electric.co.uk



© 2011 Martindale Electric Company Ltd.
Registered in England No. 3387451. E. & O.E. Rev1 LITPSI4000