

2080 Electrical Test Box



NEED TO TEST ELECTRICAL (16th Edition) INSTRUMENTS ?



Transmille's 2080 provides the quick, cost efficient solution




2080 Dimensions:
28cm x 22cm x 9cm

CHECKS INSULATION TESTERS




- 3 INSULATION RESISTOR VALUES 1M Ω • 9.9M Ω • 99M Ω (1% Accuracy)
- LED INDICATION OF TEST VOLTAGE AT 100V • 250V • 500V • 1000V
- 3 CONTINUITY RESISTOR VALUES 0.5 Ω • 2 Ω • 10 Ω (1% \pm 20m Ω Accuracy)
- AC LINE VOLTAGE OUTPUT FOR TESTING VOLTAGE MEASUREMENT

CHECKS RCD TESTERS



- FUNCTIONAL CHECK OF RCD TESTERS VIA A DEDICATED 13A SOCKET
- 3 SELECTABLE RANGES : 10mA @ 150ms • 30mA @ 150ms • 150mA @ 30ms
- INDICATORS FOR **READY** • **TRIPPED** • **OVERCURRENT**

CHECKS LOOP TESTERS



- FUNCTIONAL CHECK OF LOOP TESTERS VIA A DEDICATED 13A SOCKET
- SUPPLIED LOOP IMPEDANCE
- SUPPLIED LOOP IMPEDANCE + 1 Ω OFFSET (5% Accuracy)

WIRING CHECK ✓

- VOLTAGE INDICATIONS BETWEEN THE FOLLOWING WIRES
P-E (PHASE TO EARTH) • P-N (PHASE TO NEUTRAL)
N-E (INCORRECT WIRING)

Transmille...where technology, innovation & value meet

> Available with Calibration Certificate <

Visit our website for the full range of Transmille Products

www.transmille.com

Tel: +44 (0) 1580 890700

Fax: +44 (0) 1580 890711

E-Mail: sales@transmille.com

Website: www.transmille.com

TRANSMILLE Ltd. Unit 4, Select Business Park, Lodge Road, Staplehurst, Kent. TN12 0QW. UK.



www.transmille.com